

## System Keyboard NV-KBD60



### Features

- System keyboard designed to remotely control NOVUS® DVRs, speed domes, other NOVUS® cameras incorporating the RS-485 interface
- Protocols for DVR control: Novus-D1, Novus-D2, Novus-D3, N-Control
- Protocols for controlling speed domes and other camera types: Novus-C, Novus-C1, Novus-C2, Pelco-D
- Three-axial joystick with the zoom control ring
- 37 multi-function keys
- SHUTTLE ring, JOG dial for controlling DVR functions
- 2 x 16 digits display
- Flexible configuration of user grants, each user access secured by password
- Multi-lingual menu
- Power supply: 12 VDC

Specifications	Description
Equipment connection	NOVUS® PTZ Cameras: CAMA-I, CAMA-II & CAMA-II mini Series Other NOVUS® cameras: NVC-625DN, NVC-660DN, NVC-825DN, NVC-860DN, NVC-HDN520ZL, NVC-HDN370HZL-2 All-In-One (up to 30 cameras with various speeds) NOVUS® Digital Video Recorders: 5800, 5500, 5100, 5000 & 1100 Series, NV-DVR1014 (up to 10 devices)
Camera Protocol	Novus-C, Novus-C1, Novus-C2, Pelco-D
DVR Protocol	Novus-D1, Novus-D2, Novus-D3
Joystick	Three-axial joystick (auto-returning, zoom)
Buttons	37 multi-function keys (made of silicon)
Knob	Jog/Shuttle
Display	16 x 2 backlit LCD
External Ports	1 x RS-485 (2 x RJ-11) for connection with PTZ cameras 1 x RS-422 (RJ-11) for connection with DVRs 1 x RS-232 (D-Sub 9 Pin) for keyboard software upgrades from the PC
Power Supply	12 VDC
Power Consumption	15 W
Operating Temperature	5°C ~ 40°C
Dimensions (mm)	364 (W) x 48 (H) x 146 (D)
Weight	1.2 kg