NOVUS

IP Motor-zoom Camera with video content analysis based on Deep Learning

NVIP-2V-6502M/F





FUNCTIONS













100 mm







KEY FEATURES

- •Resolution: 2 MPX
 •Lens: motorized, auto-iris and auto-focus function, f=2.8 ~ 12 mm/F1.4
 •Human/Vehicle Object Classification
 •D/N function IR cut filter
 •Video content analysis based on Deep

- Learning
 •microSD card support

- •WDR with double scan sensor
 •Min. Illumination: 0.003 lx (0 lx, IR on)
 •IR LED, range up to 50 m

DIMENSIONS



141 mm (Ø)



The camera is dedicated to work with NOVUS 6000 series recorders. Detailed data can be found in the compatibility table available in the DOWNLOADABLE FILES tab.

Image	
Image Sensor	2 MPX CMOS sensor 1/2.8" SONY STARVIS
Number of Effective Pixels	1920 (H) x 1080 (V)
	0.003 lx/F1.4 - color mode.
Min. Illumination	0 lx (IR on) - B/W mode
Electronic Shutter	auto/manual: 1/3 s ~ 1/100000 s
Digital Slow Shutter (DSS)	up to 1/3 s
Wide Dynamic Range (WDR)	yes (double scan sensor), 120dB
Digital Noise Reduction (DNR)	2D, 3D
Defog Function (F-DNR)	yes
Highlight Compensation (HLC)	yes
Back Light Compensation (BLC)	yes
Reduction of image flicker (Antiflicker)	yes
Lens	
Lens Type	motorized, auto-iris function, f=2.8 \sim 12 mm/F1.4
Auto-focus	zoom trigger, day/night mode trigger, manual trigger
Day/Night	
Switching Type	mechanical IR cut filter
Switching Mode	auto, manual, time
Switching Level Adjustment	yes
Switching Delay	2 ~ 120 s
Switching Schedule	yes
Visible Light Sensor	yes
Network	
Stream Resolution	1920 x 1080 (Full HD), 1280 x 720 (HD), 640 x 480 (VGA), 480 x 240, 320 x 240 (QVGA)
Frame Rate	30 fps for 1920 x 1080 (Full HD) and lower resolutions
Multistreaming Mode	3 streams
Video/Audio Compression	H.264, H.264+, H.264 Smart, H.265, H.265+, H.265 Smart, MJPEG/G.711
Number of Simultaneous Connections	max. 10
Bandwidth	60 Mb/s in total
Network Protocols Support	HTTP, TCP/IP, IPv4. IPv4.\mathbb{/}6, UDP, HTTPS, Multicast, FTP, DHCP, DNS, DDNS, NTP, RTSP, UPnP, SNMP, QOS/DSCP, IEEE 802.1X, PPP0E, SMTP, RTCP, ICMP, Unicast, SSL/TLS from Internet Explorer browser
Camera Configuration	from Internet Explorer browser languages: Polish, English, Russian, and others
Compatible Software	NOVUS MANAGEMENT SYSTEM VSS, NOVUS MANAGEMENT SYSTEM AC, N Control 6000
Mobile applications	SuperLive Plus (iPhone, Android)
Other functions	
Privacy Zones	4 video mask type: single color or 1 video mask type: mosaic
Motion Detection	yes
Region of interest (ROI)	8
Video Content Analysis (VCA)	tamper, abandoned object, object disappearance, line cross, zone entrance, zone exit, object counting, face detection, pedestrian detection, cross counting, scene change, video blurred, video color cast, objects distinguishing, people counting, vehicle detection, vehicle counting
video Content Analysis (VCA)	
Image Processing	180° image rotation, sharpening, mirror effect, corridor mode, vertical flip, horizontal flip, lens distortion correction
	180° image rotation, sharpening, mirror effect, corridor mode, vertical flip, horizontal flip, lens distortion correction up to 6 s/up to 120 s
Image Processing	correction
Image Processing Prealarm/Postalarm	correction up to 6 s/up to 120 s
Image Processing Prealarm/Postalarm System Reaction to Alarm Events	correction up to 6 s/up to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card
Image Processing Prealarm/Postalarm System Reaction to Alarm Events Restoring default settings	correction up to 6 s/up to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card
Image Processing Prealarm/Postalarm System Reaction to Alarm Events Restoring default settings IR LED LED Number	correction up to 6 s/up to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software
Image Processing Prealamm/Postalarm System Reaction to Alarm Events Restoring default settings IR LED LED Number Range	correction up to 6 s/up to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software
Image Processing Prealarm/Postalarm System Reaction to Alarm Events Restoring default settings IR LED LED Number	correction up to 6 s/up to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 3 50 m 90*
Image Processing Prealarm/Postalarm System Reaction to Alarm Events Restoring default settings IR LED LED Number Range Angle Smart IR	correction up to 6 s/up to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 3 50 m
Image Processing Prealarm/Postalarm System Reaction to Alarm Events Restoring default settings IR LED LED Number Range Angle Smart IR Interfaces	correction up to 6 s/up to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 3 50 m 90° yes (hardware support)
Image Processing Prealarm/Postalarm System Reaction to Alarm Events Restoring default settings IR LED LED Number Range Angle Smart IR Interfaces Video Output	correction up to 6 s/up to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 3 50 m 90° yes (hardware support) BNC, 1.0 Vp-p, 75 Ohm
Image Processing Prealarm/Postalarm System Reaction to Alarm Events Restoring default settings IR LED LED Number Range Angle Smart IR Interfaces Video Output Audio Input/Output	correction up to 6 s/up to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 3 50 m 90° yes (hardware support) BNC, 1.0 Vp-p, 75 Ohm 1 x Jack (3.5 mm)/1 x Jack (3.5 mm) built-in mitrophone
Image Processing Prealarm/Postalarm System Reaction to Alarm Events Restoring default settings IR LED LED Number Range Angle Smart IR Interfaces Video Output Audio Input/Output Alarm Input/Output	correction up to 6 s/up to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 3 50 m 90* yes (hardware support) BNC, 1.0 Vp-p, 75 Ohm 1 x jack (3.5 mm)1 x jack (3.5 mm) bullc-in microphone 1 (NO/NCI)2 relay type (max. 12VDC/300mA)
Image Processing Prealarm/Postalarm System Reaction to Alarm Events Restoring default settings IR LED LED Number Range Angle Smart IR Interfaces Video Output Alami Input/Output Alami Input/Output Network Interface	correction up to 6 s/up to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 3 50 m 90° yes (hardware support) BNC, 1.0 Vp-p, 75 Ohm 1 x Jack (3.5 mm)/1 x Jack (3.5 mm) built-in microphone 1 (NO/NC)/1 relay type (max. 12VDC/300mA) 1 x Ethemet - R/+45 interface, 10/100 Mbit/s
Image Processing Prealarm/Postalarm System Reaction to Alarm Events Restoring default settings IR LED LED Number Range Angle Smart IR Interfaces Video Output Audio Input/Output Alarm Input/Output Network Interface Memory Card Slot	correction up to 6 s/up to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 3 50 m 90* yes (hardware support) BNC, 1.0 Vp-p, 75 Ohm 1 x jack (3.5 mm)/b x jack (3.5 mm) bullc-in microphone 1 (NO/NCI/2 relay type (max. 12VDC/300mA)
Image Processing Prealarm/Postalarm System Reaction to Alarm Events Restoring default settings IR LED LED Number Range Angle Smart IR Interfaces Video Output Audio Input/Output Alarm Input/Output Network Interface Memory Card Slot Installation parameters	correction up to 6 s/up to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 3 3 50 m 90° yes (hardware support) BNC, 1.0 Vp-p, 75 Ohm 1 x Jack (3.5 mm)/L x Jack (3.5 mm) built-in microphone 1 NO/NC/Jr relay type (max. 12VDC/300mA) 1 x Ethemet - Rj-45 interface, 10/100 Mbit/s microSD - capacity up to 256GB
Image Processing Prealarm/Postalarm System Reaction to Alarm Events Restoring default settings IR LED LED Number Range Angle Smart IR Interfaces Video Output Audio Input/Output Alarm Input/Output Network Interface Memory Card Slot Installation parameters Dimensions (mm)	correction up to 6 s/up to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 3 50 m 90* yes (hardware support) BNC, 1.0 Vp-p, 75 Ohm 1 x jack (3.5 mm)/2 x jack (3.5 mm) built-in microphone 1 (NO/NC)/I relay type (max. 12VDC/300mA) 1 x Ethernet - Ry-45 interface, 1.0/100 Mbit/s microSD - capacity up to 256GB
Image Processing Prealarm/Postalarm System Reaction to Alarm Events Restoring default settings IR LED LED Number Range Angle Smart IR Interfaces Video Output Audio input/Output Alarm input/Output Network interface Memory Card Slot Installation parameters Dimensions (mm) Weight	correction up to 6 s/up to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 3 50 m 90° yes (hardware support) BNC, 1.0 Vp-p, 75 Ohm 1 x Jack (3.5 mm)/L x Jack (3.5 mm) bulli-in microphone 1 (NO/NCI) Tealy type (max. 12VDC/300mA) 1 x Ethernet - Rj-45 interface, 10/100 Mbit/s microSD - capacity up to 256GB
Image Processing Prealarm/Postalarm System Reaction to Alarm Events Restoring default settings IR LED LED Number Range Angle Smart IR Interfaces Video Output Audio Input/Output Alarm Input/Output Alarm Input/Output Installation parameters Dimensions (mm) Weight Usegree of Protection	correction up to 6 s/up to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 3 3 90° yes (hardware support) BNC, 1.0 Vp-p, 75 Ohm 1 x Jack (3.5 mm)/1 x Jack (3.5 mm) billi-in microphone 1 (NO/NC)/I relay type (max. 12VDC/300mA) 1 x Ethemet - 8,45 interface, 10/100 Mbit/s microSD - capacity up to 256GB 141 (Φ) x 100.2 (H) 0.89 kg IP 67 (details in the user's manual)
Image Processing Prealarm/Postalarm System Reaction to Alarm Events Restoring default settings IR LED LED Number Range Angle Smart IR Interfaces Video Output Audio Input/Output Alarm Input/Output Alarm Input/Output Network Interface Memory Card Slot Installation parameters Dimensions (mm) Weight Degree of Protection Enclosure	correction up to 6 s/up to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 3 3 50 m 90° yes (hardware support) BNC, 1.0 Vp-p, 75 Ohm 1 x Jack (3.5 mm)/L x Jack (3.5 mm) built-in microphone 1 (NO/NC)/I relay type (max. 12VDC/300mA) 1 x Ethemet - Ry-45 interface, 10/100 Mbit/s microSD - capacity up to 256GB 141 (Φ) x 100.2 (H) 0.89 kg 19 67 (details in the user's manual) vandalproof IK10 impact rating aluminium, white
Image Processing Prealarm/Postalarm System Reaction to Alarm Events Restoring default settings IR LED LED Number Range Angle Smart IR Interfaces Video Output Audio Input/Output Alarm Input/Output Alarm Input/Output Installation parameters Dimensions (mm) Weight Usegree of Protection	correction up to 6 s/up to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 3 3 50 m 90° yes (hardware support) BNC, 1.0 Vp-p, 75 0hm 1 x Jack (3.5 mm)/1 x Jack (3.5 mm) billi-in microphone 1 (NO/NC)/I relay type (max. 12VDC/300mA) 1 x Ethemet - 8,45 interface, 10/100 Mbit/s microSD - capacity up to 256GB 141 (Φ) x 100.2 (H) 0.89 kg IP 67 (details in the user's manual)

7 W.
9 W (IR Illuminator on)
-30°C ~ 60°C
max. 95%, relative (non-condensing) Power Consumption Operating Temperature Humidity

The camera creates a fully functional face recognition system when used with selected NOVUS IP 6000 series recorders (models with *F* in the name).