NoVus

IP Camera with video content analysis and active

deterrence

NVIP-4H-6711/FWLAD

6000 VSS

FUNCTIONS



COMPATIBILITY




KEY FEATURES

• Resolution: 4 MPX • Lens: fixed focal, f=2.8 mm/F1.6 • active deterrence • D/N function - IR cut filter • Video content analysis based on Deep Learning • microSD card support • WDR with double scan sensor • two-way audio • Min. Illumination: 0.03 lx (0 lx, IR on) • IR LED, range up to 40 m • white LED illuminator, range up to 40 m

DIMENSIONS



220 mm



| E | Image | |
|-------|--|--|
| | Image Sensor | 4 MPX CMOS sensor 1/2.9" SmartSens |
| | Number of Effective Pixels | 2696 (H) x 1528 (V) |
| | | 0.03 lx/F1.6 - color mode, |
| | Min. Illumination | 0 lx (IR on) - B/W mode |
| h | Electronic Shutter | auto: 1/3 s ~ 1/100000 s |
| | Digital Slow Shutter (DSS) | up to 1/3 s |
| | Wide Dynamic Range (WDR) | yes (double scan sensor), 120dB |
| IJ | Digital Noise Reduction (DNR) | 2D, 3D |
| | Defog Function (F-DNR) | yes |
| | Highlight Compensation (HLC) | yes |
| | Back Light Compensation (BLC) | yes |
| | Reduction of image flicker (Antiflicker) | yes |
| | Lens | |
| | Lens Type | fixed focal. f=2.8 mm/F1.6 |
| | | inced local, 1=2.8 min/r1.0 |
| | Day/Night | |
| | Switching Type | mechanical IR cut filter |
| | Switching Mode | auto, manual, time |
| | Switching Level Adjustment | yes |
| | Switching Delay | 2 ~ 120 s |
| | Switching Schedule | yes |
| | Network | |
| | Stream Resolution | 2560 x 1440 (QHD), 2592 x 1520, 2304 x 1296, 1920 x 1080 (Full HD), 1280 x 720 (HD), 704 x 576, 640 x |
| | | 480 (VGA), 352 x 288 (CIF), 480 x 240 |
| | Frame Rate | 30 fps for each resolution |
| | Multistreaming Mode | 3 streams |
| | Video/Audio Compression | H.264, H.264+, H.265, H.265+, MJPEG/G.711 |
| | Number of Simultaneous Connections | max. 10 |
| | Bandwidth | 30 Mb/s in total |
| | Network Protocols Support | HTTP, TCP/IP, IPv4, IPv4/v6, UDP, HTTPS, FTP, DHCP, DDNS, NTP, RTSP, RTP, UPnP, SNMP, QoS, IEEE 802.1X, PPPoE, SMTP, RTCP, HTML5, RTMP |
| | Camera Configuration | from Internet Explorer, Chrome, Opera, Safari browser languages: Polish, English, and others |
| | Compatible Software | NOVUS MANAGEMENT SYSTEM VSS, NOVUS MANAGEMENT SYSTEM AC, N Control 6000 |
| | Mobile applications | SuperLive Plus (iPhone, Android) |
| | Other functions | |
| | Privacy Zones | 4 video mask type: single color or 4 video mask type: mosaic |
| | Motion Detection | yes |
| | Region of interest (ROI) | 8 |
| | Video Content Analysis (VCA) | tamper, abandoned object, object disappearance, line cross, zone entrance, zone exit, object counting, face detection, detection of people not wearing masks, cross counting, heat may, scene change, video blurred, video color cast, objects distinguishing, people counting, vehicle counting intrusion detection, target counting by area, video metadata |
| | Image Processing | 90° image rotation, 180° image rotation, sharpening, mirror effect, corridor mode, vertical flip, horizontal flip, lens distortion correction |
| | Prealarm/Postalarm | up to 6 s/up to 120 s |
| | System Reaction to Alarm Events | e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card |
| | Determent | red and blue LEDs, flashing light, built-in speaker (predefined or custom voice messages) |
| | | |
| | Restoring default settings | via web browser, using reset button, via NMS IPTool software |
| | Restoring default settings IR LED | via web browser, using reset button, via NMS IPTool software |
| | IR LED | via web browser, using reset button, via NMS IPTool software |
| | IR LED LED Number | |
| | IR LED | 1 40 m |
| | IR LED LED Number Range Smart IR | 1 |
| | IR LED LED Number Range Smart IR White light illuminator | 1 40 m yes (software support) |
| 0 | IR LED LED Number Range Smart IR White light Illuminator LED Number | 1 40 m yes (software support) 1, warm white color |
| - | IR LED LED Number Range Smart IR White light liluminator LED Number Range | 1 40 m yes (software support) 1, warm white color 40 m |
| - | IR LED LED Number Range Smart IR White light illuminator LED Number Range Smart Light | 1 40 m yes (software support) 1, warm white color |
| - | IR LED LED Number Range Smart IR White light liluminator LED Number Range | 1 40 m yes (software support) , warm white color 40 m yes (software support) |
| - | IR LED LED Number Range Smart IR White light illuminator LED Number Range Smart Light | 1 40 m yes (software support) 1, warm white color 40 m yes (software support) 1 x jack (3.5 mm)/1 x jack (3.5 mm) |
| | IR LED LED Number Range Smart IR White light liluminator LED Number Range Smart Light Interfaces Audio Input/Output | 1 40 m yes (software support) 1, warm white color 40 m yes (software support) 1 x Jack (3.5 mm)/1 x Jack (3.5 mm) bull-in microphone/speaker |
| | IR LED LED Number Range Smart IR White light illuminator LED Number Range Smart Light i Interfaces Audio Input/Output Alarm Input/Output | 1 40 m yes (software support) 1. warm white color 40 m yes (software support) 1 x Jack (3.5 mm)1 x Jack (3.5 mm) buikin microphone/speaker 1 (NO/NC)/1 relay type (max. 12VDC/300mA) |
| | IR LED LED Number Range Smart IR White light illuminator LED Number Range Smart Light Interfaces Alam Input/Output Alam Input/Output Network Interface | 1 40 m yes (software support) 1, warm white color 40 m yes (software support) 1 x jack (3.5 mm)/1 x jack (3.5 mm) bulk-in microphone/speaker 1 (NONC/1 refu type (max. 12VDC/300mA) 1 x Ethernet - RJ-45 interface, 10/100 Mbl/s |
| - | IR LED LED Number Range Smart IR White Iight Illuminator LED Number Range Smart Light Interface Audio Input/Output Alarm Input/Output Metwork Interface Memory Card Slot | 1 40 m yes (software support) 1. warm white color 40 m yes (software support) 1 x Jack (3.5 mm)/1 x Jack (3.5 mm) buil:n microphone/speaker 1 (NO/NC)/1 relay type (max. 12VDC/300mA) |
| - | IR LED LED Number Range Smart IR White light illuminator LED Number Range Smart Light Interfaces Alam Input/Output Alam Input/Output Network Interface | 1 40 m yes (software support) 1, warm white color 40 m yes (software support) 1 x jack (3.5 mm)/1 x jack (3.5 mm) bulk-in microphone/speaker 1 (NONC/1 refu type (max. 12VDC/300mA) 1 x Ethernet - RJ-45 interface, 10/100 Mbl/s |
| - | IR LED LED Number Range Smart IR White light iluminator LED Number Range Smart Light i Interfaces Audio Input/Output Alarm Input/Output Alarm Input/Output Network Interface Memory Card Siot Installation parameters Dimensions (mm) | 1 40 m yes (software support) 1, warm white color 40 m yes (software support) 1 x jack (3.5 mm)/1 x jack (3.5 mm) bulk-in microphone/speaker 1 (NONC/1 refu type (max. 12VDC/300mA) 1 x Ethernet - RJ-45 interface, 10/100 Mbl/s |
| 81 mm | IR LED LED Number Range Smart IR White light illuminator LED Number Range Smart Light Interfaces Audio Input/Output Alarm Input/Output Metwork Interface Memory Card Slot Installation parameters | 1 40 m yes (software support) 1, warm white color 40 m yes (software support) 1 x Jack (3.5 mm)/1 x Jack (3.5 mm) bulk-in microphone/speaker 1 (NO/NC)/1 relay type (max. 12VDC/300mA) 1 x Ethemet - RJ-45 interface, 10/100 Mbit/s microSD - capacity up to 256GB |



www.novuscctv.com

| aluminium, white, fully cable managed wall mount bracket in-set included , IK10 impact rating |
|---|
| 12 VDC, PoE (IEEE 802.3af, Class 3) |
| TVS 4000 V |
| 5 W, 9 W (W illuminator on), 9 W (white light illuminator on), 11 W (IR illuminator and active deterrence functions enabled) |
| -30°C ~ 60°C |
| max. 95%, relative (non-condensing) |
| |

The camera creates a fully functional face recognition system when used with selected NOVUS IP 6000 series recorders (models with "F" in the name).