



# IP Recorder

## NVR-4532-H4/F



4000

VSS  
IP

### FUNCTIONS



### KEY FEATURES


- 32 x video and audio channels
- Recording speed up to 960 fps at 3840 x 2160
- Recorded stream size: 320 Mb/s in total from all cameras
- 4 x internal place for HDD mounting
- 2 x monitor outputs (HDMI 4K UltraHD, VGA)
- Face recognition

### DIMENSIONS



326 mm

66 mm



378 mm



Video	
IP Cameras	up to 32 channels at 3840 x 2160 resolution (video + audio)
Maximum Supported Camera Resolution	3840 x 2160 3000 x 3000 for fisheye cameras
Compression	H.264, H.264+, H.265, H.265+
Monitor Output	main (split screen, full screen, sequence): 1 x HDMI (4K UltraHD), 1 x VGA (up to 2 monitors simultaneously) spot: 1 x VGA (FullHD)
Dualstreaming Support	yes
Fisheye Support	yes, 2000/4000 IP series cameras
Audio	
Audio Input/Output	1 x line-in (RCA) / 1 x HDMI, 1 x line-out (RCA)
Recording	
Recording Speed	960 fps (32 x 30 fps for 3840 x 2160 and lower)
Stream Size	320 Mb/s in total from all cameras
Recording Mode	continuous, triggered by: manual, alarm input, motion detection, face recognition, intelligent image analysis functions, PIR alarm
Prealarm/Postalarm	up to 3 s/up to 600 s
Display	
Display Speed	960 fps (32 x 30 fps)
Playback	
Playback Speed	480 fps (16 x 30 fps)
Recorded Data Search	by date/time, events, image analysis events, motion in a defined area, related to face recognition, tags
Backup	
Backup Methods	USB port (HDD or Flash memory), network
Backup File Format	JPG, BMP, PNG, MP4, AVI, RF
Storage	
Internal Storage	available mount: 4 x HDD 3.5" 14 TB SATA
Total Internal Capacity	56 TB
External storage	1 x eSATA
Total External Capacity	32 TB
Alarm	
Internal Alarm Input/Output	16/1 relay type
Camera Alarm Input/Output	supports IP camera's alarm input/output
System Reaction to Alarm Events	buzzer, e-mail, alarm output activation, screen message, recording activation, PTZ, Full Screen, FTP picture upload, FTP video upload, picture to Cloud, video to Cloud
Intelligent image analysis	
Supported Functions	Exception, Tripwire, Zone entrance, Abandoned Object, Object Disappearance, Face Detection, Pedestrian Detection, Cross Counting, Face Recognition, Sound detection, Perimeter Intrusion Detection by pedestrian or vehicle, Line Cross Detection by pedestrian or vehicle
Network	
Network Interface	2 x Ethernet - RJ-45 interface, 10/100/1000 Mbit/s
Network Protocols Support	HTTP, TCP/IP, IP4/v6, HTTPS, FTP, DHCP, DNS, DDNS, NTP, RTSP, UPnP, SNMP, PPPoE, SMTP, P2P
PC/MAC Software	NOVUS MANAGEMENT SYSTEM AC, NMS, Internet Explorer, NHDR-5000 Viewer, N Control 4000 Viewer, N Control 4000
Mobile applications	RxCamView (iPhone, Android)
Number of Simultaneous Connections	up to 96 clients
Bandwidth	320 Mb/s in total to all client workstations
PTZ	
PTZ Functions	pan/tilt/zoom, preset commands, patterns
Auxiliary Interfaces	
USB Ports	1 x USB 3.0, 2 x USB 2.0,
Operating system	
Operating System	Linux
OSD	languages: Polish, English, others
Control	PC mouse and IR remote controller (in-set included), network
System Diagnostic	automatic control of: HDDs, network, camera connection loss
Security	password protection, IP filtering
Installation parameters	
Dimensions (mm)	378 (W) x 66 (H) x 326 (D)
Weight	2.5 kg (without HDDs)
Power Supply	12 VDC (100 ~ 240 VAC/12 VDC PSU in-set included)
Power Consumption	60 W (with 4 HDDs)
Operating Temperature	-10°C ~ 45°C

Intelligent image analysis, dualstream mode, PTZ control, motion detection and alarm inputs / outputs functions depends on the functionality of the camera and the capabilities of the communication protocol. The recorder is dedicated to work with Novus 2000 and 4000 series IP cameras and achieves the best functionality with them. Detailed data on camera compatibility with recorders and compatible hard drives can be found in the compatibility tables available in the DOWNLOADABLE FILES tab.  
Display and playback speeds are achieved using dual stream.  
One of the functions: SPOT monitor, Face Recognition can be switched on at the same time.