## NoVus

### 8 MPX IP Motor-zoom Camera with video content analysis based on Deep Learning

NVIP-8VE-6502M/F-II

# 6000 VSS

#### FUNCTIONS



#### **KEY FEATURES**

•Resolution: 8 MPX (4K Ultra HD) •Lens: motorized, auto-focus function, f=2.8 ~ 12 mm/F1.4 •Human/Vehicle Object Classification •D/N function - IR cut filter •Video content analysis based on Deep Learning •microSD card support •WDR with double scan sensor •Min. Illumination: 0.015 lx (0 lx, IR on) •IR LED, range up to 50 m

### DIMENSIONS



112 mm (Ø)



The camera is dedicated to work with NOVUS 6000 series recorders. Detailed data can be found in the compatibility table available in the DOWNLOADABLE FILES tab.

Image	
Image Sensor	8 MPX CMOS sensor 1/2.8" SONY STARVIS
Number of Effective Pixels	3864 (H) × 2192 (V)
Min. Illumination	0.015 lx/F1.4 - color mode, 0 lx (IR on) - B/W mode
Electronic Shutter	auto/manual: 1/3 s ~ 1/100000 s
Digital Slow Shutter (DSS)	up to 1/3 s
Wide Dynamic Range (WDR)	yes (double scan sensor), 120dB
Digital Image Stabilization (DIS)	yes
Digital Noise Reduction (DNR)	3D
Defog Function (F-DNR)	yes
Highlight Compensation (HLC)	ves
Back Light Compensation (BLC)	ves
Reduction of image flicker (Antiflicker)	yes
Lens	
Lens Type	motorized, f=2.8 ~ 12 mm/F1.4
Auto-focus	zoom trigger, day/night mode trigger, manual trigger
DORI	zoon eigger, aajnigie node eigger, nande eigger
	for f = 2.8mm - D: 85m, O: 34m, R: 17m, I: 8m
DORI (Detection, Observation, Recognition, Identification)	for f = 12mm - D: 289m, O: 116m, R: 58m, I: 29m
Day/Night	
Mode	day/night switching: mechanical IR cut filter
Switching Mode	auto, manual, time
Switching Level Adjustment	yes
Switching Delay	2 ~ 120 s
Switching Schedule	yes
Visible Light Sensor	yes
Network	
Stream Resolution	3840 x 2160 (4K Ultra HD), 3072 x 2048, 2560 x 1440 (QHD), 2592 x 1520, 2592 x 1944, 2304 x 1296, 19 x 1080 (Full HD), 1280 x 720 (HD), 704 x 576, 640 x 480 (VGA), 352 x 288 (CIF), 480 x 240
Frame Rate	30 fps for each resolution
Multistreaming Mode	number of streams: 3
Video/Audio Compression	H.264, H.264+, H.265, H.265+, MIPEG/G.711
Number of Simultaneous Connections	max, 10
Bandwidth	82 Mb/s in total
Network Protocols Support	HTTP, TCP/IP, IPv4, IPv4/v6, UDP, HTTPS, FTP, DHCP, DNS, DDNS, NTP, RTSP, RTP, UPnP, SNMP, QoS, IEEE 802.1X, PPPOE, SMTP, RTCP, SSL/TLS, HTML5, RTMP
Camera Configuration	from Internet Explorer, Edge, Firefox, Chrome, Opera, Safari browser languages: Polish, English, and others
Compatible Software	NOVUS MANAGEMENT SYSTEM VSS, NOVUS MANAGEMENT SYSTEM AC, N Control 6000
Mobile applications	SuperLive Plus (iPhone, Android)
Video Analytics	
Functions	tamper, abandoned object, object disappearance, line cross, zone entrance, zone exit, object counting, loiter, multi loiter, face detection, detection of people not wearing masks, cross counting, heat map, scene change, video blurred, video color cast, objects distinguishing, people counting, vehicle counting, intrusion detection, target counting by area, video metadata, lilegal parking detection
Other functions	
Security	video encryption, configuration encryption, IEEE 802.1X support, HTTPS support, Basic authorization for HTTP/RTSP, Digest authorization for HTTP/RTSP, MAC/IP address filtering, force change of default password
Privacy Zones	4 video mask type: single color or 4 video mask type: mosaic
Motion Detection	yes
Region of interest (ROI)	8
Audio Detection	yes
	yes 90° image rotation, 180° image rotation, sharpening, mirror effect, corridor mode, vertical flip, horizontal flip, lens distortion correction
Audio Detection	90° image rotation, 180° image rotation, sharpening, mirror effect, corridor mode, vertical flip, horizontal
Audio Detection Image Processing	90° image rotation, 180° image rotation, sharpening, mirror effect, corridor mode, vertical flip, horizontal flip, lens distortion correction
Audio Detection Image Processing Prealarm/Postalarm	9° image rotation, 180° image rotation, sharpening, mirror effect, corridor mode, vertical flip, horizontal flip, lens distortion correction up to 6 s(up to 120 s
Audio Detection Image Processing Prealarm/Postalarm System Reaction to Alarm Events	90° image rotation, 180° image rotation, sharpening, mirror effect, corridor mode, vertical flip, horizontal flip, lens distortion correction up to 6 s/up to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card
Audio Detection Image Processing Prealarm/Postalarm System Reaction to Alarm Events Restoring default settings	90° image rotation, 180° image rotation, sharpening, mirror effect, corridor mode, vertical flip, horizontal flip, lens distortion correction up to 6 s/up to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card
Audio Detection Image Processing Prealarm/Postalarm System Reaction to Alarm Events Restoring default settings IR LED	9° image rotation, 180° image rotation, sharpening, mirror effect, corridor mode, vertical flip, horizontal flip, lens distortion correction up to 6 s/up to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software
Audio Detection Image Processing Prealarm/Postalarm System Reaction to Alarm Events Restoring default settings IR LED LED Number	9° image rotation, 180° image rotation, sharpening, mirror effect, corridor mode, vertical flip, horizontal flip, lens distotion correction up to 6 slup to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 3
Audio Detection Image Processing Prealamu/Postalarm System Reaction to Alarm Events Restoring default settings IR LED LED Number Range	90° image rotation, 180° image rotation, sharpening, mirror effect, corridor mode, vertical flip, horizontal flip, lens distortion correction up to 6 slup to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 3
Audio Detection Image Processing Prealarm/Postalarm System Reaction to Alarm Events Restoring default settings IR LED LED Number Range Smart IR	90° image rotation, 180° image rotation, sharpening, mirror effect, corridor mode, vertical flip, horizontal flip, lens distortion correction up to 6 slup to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 3 50 m yes (software support) 1 x lack (3.5 mm)/-
Audio Detection Image Processing Prealamu/Postalarm System Reaction to Alarm Events Reastoring default settings IR LED LED Number Range Smart IR Interfaces	90° image rotation, 180° image rotation, sharpening, mirror effect, corridor mode, vertical flip, horizontal flip, iers distortion correction up to 6 s(up to 120 s e-mail, e-mail, with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 3 50 m yes (software support)
Audio Detection Image Processing Prealamu/Postalarm System Reaction to Alarm Events Reactoring default settings IR LED LED LED LED Mumber Smart IR Interfaces Audio Input/Output	90° image rotation, 180° image rotation, sharpening, mirror effect, corridor mode, vertical flip, horizontal flip, lens distortion correction up to 6 slup to 120 s e-mail, e-mail with attachment, saving file on FTP server, saving file on SD card via web browser, using reset button, via NMS IPTool software 3 50 m yes (software support) 1 x Jack (3.5 mm)/- buil-in microphone



Dimensions (mm)	112 (Φ) x 100 (H)
Weight	0.7 kg
Degree of Protection	IP 67 (details in the user's manual)
Enclosure	vandalproof, IK10 impact rating, aluminium, white enclosure type: 6VE-M
Power Supply	12 VDC, PoE (IEEE 802.3af, Klasa 3)
Surge protection	TVS 4000 V
Power Consumption	7 W, 11 W (IR illuminator on)
Operating Temperature	-30°C ~ 60°C
Humidity	max. 95%, relative (non-condensing)
Operating Temperature	11 Ŵ (IR illuminator on) -30°C ~ 60°C

The camera creates a fully functional face recognition system when used with selected NOVUS IP 6000 series recorders (models with "F" in the name).